

Earth Ground Resistance Tester Kit

 **Includes all hardware necessary to measure earth ground**
In 3 ranges from 0.01 to 2000Ω

Features:

- 3-1/2 Digit (1999 count) multifunction LCD with Data Hold
- Measures Earth Resistance in three ranges
- 2mA (800Hz) Test Current and Frequency
- 0 to 200VAC (40 to 500Hz) AC Earth Voltage/Frequency
- Auto power off, 3 minute Timer
- Overload Protection
- Open circuit, overrange and low battery indications
- Complete with test leads, auxiliary earth bars, heavy duty case, and six 1.5V AA batteries



Check resistance between earth and grounding rod.

Specifications

| | |
|--------------------------------|-----------------------------------|
| Earth Ground Resistance ranges | 20 / 200 / 2000 Ω |
| Basic Accuracy | ±(2%rdg+2d) |
| Resolution | 0.01 / 0.1 / 1 |
| Test Current / Frequency | 2mA (800Hz) |
| AC Earth Voltage / Frequency | 0 to 200VAC (40 to 500Hz) |
| Basic Accuracy | ±(1%rdg+2d) |
| Power supply | Six 1.5V 'AA' Batteries |
| Dimensions | 6.4 x 3.9 x 2" (163 x 100 x 50mm) |
| Weight | 25.7oz (800g) |

Ordering Information:

- 382152.....Earth Ground Resistance Tester Kit
382152-NIST382152 with Calibration Traceable to NIST
382153.....Replacement Earth Bars (2pk)
382154.....Replacement Set of Leads

